


# User Manual of SKMEI Model #1251



## A. Features :

- ◆ 13 Digits, Hour, Minutes, Seconds, Month, Day and Week
- ◆ Daily Alarm, Chime Hourly and Snooze Function
- ◆ 2 / 24H format selectable, Auto Calendar
- ◆ 1/100 second Chronograph with split functions
- ◆ Count Down (Upper limit : 24H)
- ◆ Dual Time
- ◆ EL backlight

## B. Operational Manual :



1. At any state, press A key EL backlight for 3s.

## 2. Real Time :

- ◆ Time Setting
  - a) Press and hold C key for 2s to time setting state and "Second" flashing, press D key to zero; Press B key to select item as following sequence :  
 Second → Hour → Minute → Year → Month → Day
  - b). Press D key to adjust the flashing item,
  - c). Press C key to return to Real Time Mode.
  - d). Press D key while the seconds are in the range of 30 to 59 resets them to 00 and adds 1 to the minutes. In the range of 00 to 59 resets them to 00 and adds to the minutes. In the range of 00 to 29, the minutes are unchanged.
  - e) 12/24-Hour format : In the timekeeping Mode, Use D to toggle between 12-hour (12H) and 24-hour (24H) timekeeping.

## 3. Daily Alarm :

- ◆ In Real Time Mode, press B key enter into Alarm Mode
- ◆ Press C key to turn on/off Alarm (A) and Snooze (Snz), In Alarm Mode, press button D, then C to turn on/off (A) hourly chime
- ◆ Alarm setting  
 Press and hold C key for 2s to select "Hour" setting; Press B key to select "Minute" setting; Press D key to adjust the flashing item.  
 Hour → Minute

## 4. Chronograph :

- ◆ In Real Time Mode, press B key twice enter into Chronograph Mode
- ◆ Press D key to Start/Stop running; When stop, press C key to zero.
- ◆ When running, press C key to split Counting. Then press D key to exit split count, and stop counting; When exit split count, press C key to zero.

## 5. Dual Time :

- ◆ Dual Time setting  
 In Real Time mode, Press B key 3 times to enter Dual Time Mode, Press and hold C key for 2s to select "Hour" setting, Press B key to select "Minute" setting, Press D key to adjust the flashing item, Press C key again to finish setting, and return to Dual Time displaying mode.

## 6. Timer Mode :

- ◆ In Real Time Mode, press B key four times enter into Timer mode
- ◆ Press D key to Start/Stop countdown
- ◆ When stop the countdown, press C key back to the first setting time
- ◆ Timer alarm sounds for about 10s when counting down to 0:00:00. The timer is automatically reset to its starting value after the alarm stops.
- ◆ Press C key 2s enter into countdown time setting
  - a). Press B key to adjust "Hour" and then "Minute"  
 Hour → Minute
  - b). Press D key to adjust the flashing item
  - c). Press C key to confirm